

Small size. Big impact.

Eaton's comprehensive line of XT IEC power controls



Powering Business Worldwide

The **XT** Line of IEC Power Control, consisting of contactors, overload relays, mini controls, manual motor protectors and combination style starters, is one of the world's newest and most complete IEC Power Control product lines on the market. The **XT** applies new technology and design to help OEMs address five basic needs:

Improving production

Toolless assembly

- Requires no tools to assemble
- Applies to B-Frame (10 hp, 15A) reversing and star-delta contactors, combination style starters and surge suppressor accessories

Combination style starters

- One unit replaces traditional breaker/fuse block with contactor and overload, saving installation time and effort

Coil terminations

- Easily accessible coil terminations in the front of the contactor make installation, testing, and replacement much easier and safer

Lowering material costs

Small contactors

- Smallest 10 hp contactor on the market
- All **XT** DC controlled contactors have the same depth as AC controlled **XT** contactors
- Reduced panel space can help decrease enclosure size and costs

Side-by-side mounting

- Low coil consumption allows for side-by-side mounting
- Reversing contactors require no additional width for the mechanical interlock
- Reduced panel space can help decrease enclosure size and costs

Combination style starters

- Replaces traditional breaker/fuse block with contactor and overload
- Reduced panel space can help decrease enclosure size and costs

Electronic coils

- Efficient coil design—185A to 2000A
- **XT** contactors have low coil consumption, translating to smaller, less expensive CPTs and power supplies
- Unique control scheme allows for direct control from a PLC or low consumption command device
- Can eliminate the need for a large CPT and interposing relay leading to a reduction in component costs, and smaller enclosure size and costs

Surge suppression

- Surge suppression built-in to electronic coils
- Included in all DC coils
- Included in all AC coils above 185A

Improving equipment performance

Electronic DC coils

- Larger pick-up voltage tolerance and operation range
- Consistent switch-on and switch-off
- Voltage dip ride-through
- Surge suppression included

Better motor performance and protection

- Phase loss and phase imbalance protection conserve motor life and ensure optimum motor performance

Excellent quality performance

- **XT** has best in class warranty PPM (parts per million) when compared with similar electrical manufacturers

Improving equipment usability

Slideable DIN rail adapter

- Allows for easy component replacement without removal of adjacent components and terminations
- Allows for last minute changes and design flexibility

Visible coil power indication

- Enables easy troubleshooting and testing of contactor operation
- Applies to contactors and combination style starters up to 150A

Overload selectability

- 5:1 ratio current adjustment range, selectable trip class (5, 10, 20, 30) and selectable reset style as standard, allowing for greater flexibility using less part numbers

Improving equipment safety

Better termination

- Top/bottom dual chamber terminals provide a more secure termination for wires of differing size, minimizing the chance that a wire could become loose
- Applies to contactors up to 500A and manual motor protectors (MMPs)/combination style controllers up to 65A

Removable electrical bridge

- Removing electrical bridge ensures starter is off-line during servicing
- Applies to combination style starters up to 15A

Finger-safe and back-of-hand proof

- Requires no additional shield accessories
- Applies to contactors up to 150A and MMPs up to 65A



Frame	Contactors										Overload Relays			Auxiliary Contacts			Accessories				
	Catalog Number	Aux Contact	UL/CSA Ratings				General Purpose Amps	IEC Ratings		Catalog Number	FLA Adjustment Range (A)	Catalog Number	Mounting Location	Contact Configuration	Catalog Number	Reversing Link Kits Catalog Number					
			hp 200V 3-P	hp 230V 3-P	hp 460V 3-P	hp 600V 3-P		AC-3 (A)	AC-1 (A)												
A	XTMC6A10	1NO	1.5	2	3	3	15	6.6	20	XTOM-Thermal	XTOMP16AC1	0.1-0.16	XTMCXFA11	Front	1NO/1NC	XTMCXML	XTMCXRL				
	XTMC6A01	1NC	1.5	2	3	3	15	6.6	20		XTOMP24AC1	0.16-0.24		XTMCXFA20	Front			2NO			
	XTMC9A10	1NO	2	3	5	5	15	8.8	20		XTOMP40AC1	0.24-0.4		XTMCXFA02	Front			2NC			
	XTMC9A01	1NC	2	3	5	5	15	8.8	20		XTOMP60AC1	0.4-0.6		XTMCXFA40	Front			4NO			
B	XTCE007B10	1NO	1.5	2	3	5	20	7	20	XTOB-Thermal	XTOB001BC1	0.6-1	XTCEXFA11	Front	1NO/1NC	XTCEXMLB	XTCEXRLB				
	XTCE007B01	1NC	1.5	2	3	5	20	7	20		XTOB1P6BC1	1-1.6		XTCEXFA20	Front			2NO			
	XTCE009B10	1NO	3	3	5	7.5	20	9	20		XTOB2P4BC1	1.6-2.4		XTCEXFA02	Front			2NC			
	XTCE009B01	1NC	3	3	5	7.5	20	9	20		XTOB004BC1	2.4-4		XTCEXFA40	Front			4NO			
	XTCE012B10	1NO	3	3	10	10	20	12	20		XTOB006BC1	4-6		XTCEXFA31	Front			3NO/1NC			
	XTCE012B01	1NC	3	3	10	10	20	12	20		XTOB010BC1	6-10		XTCEXFA22	Front			2NO/2NC			
	XTCE015B10	1NO	5	5	10	10	20	15.5	20	XTOB012BC1	9-12	XTCEXFA04		Front	4NC						
	XTCE015B01	1NC	5	5	10	10	20	15.5	20	XTOB016BC1	12-16										
	C	XTCE018C10	1NO	5	5	10	15	40	18	35	XTOB-Thermal	XTOB004CC1		2.4-4	XTCEXSC11 (for C Frame only)			Side	1NO/1NC	XTCEXMLC	XTCEXRLC
		XTCE018C01	1NC	5	5	10	15	40	18	35		XTOB006CC1		4-6							
XTCE025C10		1NO	7.5	10	15	20	40	25	40	XTOB010CC1		6-10									
XTCE025C01		1NC	7.5	10	15	20	40	25	40	XTOB016CC1		10-16									
XTCE032C10		1NO	10	10	20	25	40	32	40	XTOB024CC1	16-24										
XTCE032C01		1NC	10	10	20	25	40	32	40	XTOB032CC1	24-32										
										XTOB038CC1	24-38										
D	XTCE040D00	—	10	15	30	40	55	40	50	XTOB-Thermal	XTOB024DC1	16-24	XTCEXFBG11	Front	1NO/1NC	XTCEXMLD	XTCEXRLD				
	XTCE050D00	—	15	20	40	50	65	50	65		XTOB040DC1	24-40		XTCEXFBG20	Front			2NO			
	XTCE065D00	—	20	25	50	60	80	65	80		XTOB057DC1	40-57		XTCEXFBG02	Front			2NC			
	XTCE072D00	—	20	25	50	60	80	72	80		XTOB065DC1	50-65		XTCEXFBG40	Front			4NO			
F-G	XTCE080F00	—	25	30	60	75	125	80	90	XTOB-Thermal	XTOB075DC1	65-75	XTCEXSB11	Side	1NO/1NC	XTCEXMLG	XTCEXRLG				
	XTCE095F00	—	25	40	75	100	125	95	110		XTOE1P6CCS	0.33-1.65									
	XTCE115G00	—	40	50	100	100	160	115	130		XTOE005CCS	1-5									
	XTCE150G00	—	40	60	125	125	160	150	160	XTOE020CCS	4-20										
	XTCE170G00	—	40	60	125	125	225	170	185	XTOE045CCS	9-45										
										XTOE100DCS	20-100										

For a complete listing of products and ratings, please see the XT IEC Power Control Catalog Supplement, CA03407001E.

● Replace underscore with coil voltage suffix from table below.

Frame	Relays			Auxiliary Contacts			Accessories
	Catalog Number	Contact Configuration	Thermal Current I _{th}	Catalog Number	Mounting Location	Contact Configuration	
A	XTRM10A40	4NO	10	XTMCXFA11	Front	1NO/1NC	XTMCXML
	XTRM10A31	3NO/1NC	10	XTMCXFA20	Front	2NO	
	XTRM10A22	2NO/2NC	10	XTMCXFA02	Front	2NC	
				XTMCXFA40	Front	4NO	
				XTMCXFA31	Front	3NO/1NC	
B	XTRE10B40	4NO	16	XTCEXFA11	Front	1NO/1NC	XTCEXMLB
	XTRE10B31	3NO/1NC	16	XTCEXFA20	Front	2NO	
	XTRE10B22	2NO/2NC	16	XTCEXFA02	Front	2NC	
				XTCEXFA40	Front	4NO	
				XTCEXFA31	Front	3NO/1NC	
				XTCEXFA22	Front	2NO/2NC	
			XTCEXFA04	Front	4NC		

● Replace underscore with coil voltage suffix from table at right.



XT
IEC Power Control
Global products mean global solutions

DIN Rail/Panel Mount Adapter for Thermal (XTOB) Overload Relay

Catalog Number	Frame Size
XTOBXDINC	C
XTOBXDIND	D

Common Coil Voltage	
Voltage	Suffix Code
120 Vac	A
240 Vac	B
24 Vac	T
24 Vdc	TD

Frame	Manual Motor Protectors			Auxiliary Contacts			Enclosures			Accessories			
	Catalog Number	FLA Adjustment Range		Catalog Number	Mounting Location	Contact Configuration	Catalog Number	Protection	Description	Catalog Number	Description	Catalog Number	Description
B	XTPBP16BC1	0.1-0.16	XTPAXFA11 XTPAXFA10	XTPAXFA11 XTPAXFA10	Front Front	1NO/1NC 1NO	Fits MMP Only, No Side Mount Accessories			Three-Phase Commoning Links			
	XTPBP25BC1	0.16-0.25					XTPBXENAS65			XTPAXIT			
	XTPBP40BC1	0.25-0.4					XTPBXENAS65			XTPAXCLKA2			
	XTPBP63BC1	0.4-0.63								XTPAXCLKA3			
	XTPB001BC1	0.63-1								XTPAXCLKA4			
	XTPB1P6BC1	1-1.6								XTPAXCLKA5			
	XTPB2P5BC1	1.6-2.5								XTPAXLSA			
	XTPB004BC1	2.5-4								XTPAXPCB			
	XTPB6P3BC1	4-6.3								XTCE...B			
	XTPB010BC1	6.3-10								XTPAXRHMB			
	XTPB012BC1	8-12								XTPAXTCC			
	XTPB016BC1	10-16								XTCE...C			
B	XTPRP16BC1	0.1-0.16	XTPAXSATR20 XTPAXSATR02	XTPAXSA11 XTPAXSA12 XTPAXSA21	Side Side Side	1NO/1NC 1NO/2NC 2NO/1NC	XTPAXENAS55B			XTPAXLSAD			
	XTPRP25BC1	0.16-0.25					XTPAXENAS55RY			XTPAXTPCD			
	XTPRP40BC1	0.25-0.4								XTCE...D			
	XTPRP63BC1	0.4-0.63											
	XTPR001BC1	0.63-1											
	XTPR1P6BC1	1-1.6											
	XTPR2P5BC1	1.6-2.5											
	XTPR004BC1	2.5-4											
	XTPR6P3BC1	4-6.3											
	XTPR010BC1	6.3-10											
	XTPR012BC1	8-12											
	XTPR016BC1	10-16											
D	XTPR020BC1	16-20				XTPAXENCSD65B			XTPAXCLKA2D				
	XTPR025BC1	20-25				XTPAXENCSD65RY			XTPAXCLKA3D				
	XTPR032BC1	25-32							XTPAXCLKA4D				
	XTPR016DC1	10-16											
	XTPR025DC1	16-25											
	XTPR032DC1	25-32											

Screw Type Links:
Frame B XTPR.B+XTCE.B:
XTPAXEMCB
Frame B MMP to C Contactor
XTPR.B+XTCE.C:
XTPAXEMCC

We make what matters work.*

* At Eaton, we believe that power is a fundamental part of just about everything people do. Technology, transportation, energy and infrastructure—these are things the world relies on every day. That's why Eaton is dedicated to helping our customers find new ways to manage electrical, hydraulic and mechanical power more efficiently, safely and sustainably. To improve people's lives, the communities where we live and work, and the planet our future generations depend upon. Because that's what really matters. And we're here to make sure it works.

See more at [Eaton.com/whatmatters](https://www.eaton.com/whatmatters)

For more information, visit

[Eaton.com/xt](https://www.eaton.com/xt)

Eaton
1000 Eaton Boulevard
Cleveland, OH 44122
United States
[Eaton.com](https://www.eaton.com)

© 2018 Eaton
All Rights Reserved
Printed in USA
Publication No. SA03407020E / Z21502
September 2018

Eaton is a registered trademark.

All other trademarks are property of their respective owners.